

EECE.3170: Microprocessor Systems Design I

Fall 2019

Homework 2

Due **Wednesday, 9/25/19**

Notes:

- All of your work should be submitted using the appropriate link in Blackboard.
- While typed solutions are preferred, handwritten solutions are acceptable. However, your handwritten work must be scanned and submitted electronically.
- Your submission must be in a single file. Archive files will not be accepted—if you're scanning handwritten pages, combine all pages in a Word document or PDF file.
- This assignment is worth 100 points.

Assume the state of an x86 processor's registers and memory are:

	Address	Lo		Hi	
EAX: 0xEECE3170	0x20100	10	00	08	00
EBX: 0x00000001	0x20104	10	10	FF	FF
ECX: 0x00000002	0x20108	08	00	19	91
EDX: 0x00000004	0x2010C	20	40	60	80
ESI: 0x00020100	0x20110	02	00	AB	0F
EDI: 0x00020110	0x20114	30	99	11	55
	0x20118	40	AA	7C	EE
	0x2011C	FF	BB	42	D2
	0x20120	30	CC	30	90

What is the result of each of the instructions listed below? Assume that the instructions execute in sequence—in other words, the result of each instruction may depend on the results of earlier instructions. Correctly evaluating each instruction will earn you **10 points**.

Note that you may assume any constant values shown using less than 32 bits are zero-extended to 32 bits if necessary (for example, 0x000F = 0x0000000F).

```
MOV    DL, 0xFE
MOV    DH, AL
MOVSX BX, BYTE PTR [ESI+0x000F]
MOV    [EDI+ECX], EBX
MOV    [ESI+4*ECX], AX
XCHG  CL, [ESI]
MOVZX EAX, WORD PTR [EDI+ECX]
MOV    DX, [EDI+0xFFFFFFFF]
LEA   ECX, [ESI+EBX+0x0017]
MOVSX EBX, BYTE PTR [ESI+4]
```